

RINI SNEAK

27-Feb.-2020

1.0 LED

LED 7/10W | 350-500mA | COB 3-step | excl. power supply

CE IP44 0.3m E

white texture	154261W_
black texture	154261B_

LIGHT COLOUR

2700K >90CRI 460-620lm 18Vf	3
3000K >90CRI 480-640lm 18Vf	5
1800-2850K >95CRI 290-390lm 16Vf	9

ALWAYS USE
for power supplies please see our catalogue

1.0 PAR16

Max. 35W | GU10 | 100-240VAC

CE IP44 0.9m E

white texture	154220W0
black texture	154220B0

OPTIONAL
for PAR16 lamps please our catalogue

1.0 MR16

QR-CBC51 Max. 35W | GU5.3 | 12V | excl. transformer


CE IP44 0.9m E

white texture	154210W0
black texture	154210B0

ALWAYS USE
for transformers please see our catalogue


1.0 LED

②








1.0 PAR16

④




1.0 MR16

①




IP20




IP rating when installed.
(Fixture is IP20 for the recessed part & IP44 at the visible side)

DIMENSIONS


2.0 LED



2.0 PAR16



2.0 MR16




MOUNTING INSTRUCTION

- Mount the light source in the housing and fix it with the front ring.
- Make a hole in the ceiling according to the prescribed dimensions.

③ POWER CONNECTION

SERIAL CONNECTION - for LED

Always use a power supply according to the specifications of the LED module.



PARALLEL CONNECTION - for PAR16



- Push up the springs and insert the fixture in the ceiling hole.



FOR HALOGEN LAMPS:

- The mounting height for the luminaire should be more than 2.5m.
- luminaires not suitable for covering with thermally insulating material.
- luminaires not suitable for direct mounting on normally flammable surfaces (suitable only for mounting on non-combustible surfaces.)



WEVER & DUCRÉ
LIGHTING

www.weverducre.com

Wever & Ducre bvba Spinnerijstraat 99/21 8500 Kortrijk

**INSTALLATION
INSTRUCTIONS**